Amendments to the Claims

- 1 1. (currently amended) A method for generating FSK symbols in a
- 2 communications network, comprising:
- partitioning a plurality of complex values representing OFDM tones
- 4 into a plurality of groups;
- 5 assigning a distinct energy to each group of complex values;
- 6 applying an OFDM modulator to the plurality of complex values
- 7 having the assigned distinct energies to generate FSK symbols
- 8 corresponding to the plurality of groups, in which a duration of each FSK
- 9 symbol is smaller or equal to a duration of an OFDM symbol for which the
- 10 OFDM modulator is designed; and
- 11 transmitting the FSK symbols serially.
 - 1 2. (original) The method of claim 1, in which the OFDM modulator includes
 - 2 a single IFFT, and the distinct energies are assigned to each group according
 - 3 to a data stream.
 - 3. (original) The method of claim 1, in which the OFDM modulator includes
 - 2 a plurality of IFFTs operating in parallel, and outputs of the plurality of
- 3 IFFTs are selected according to a data stream.
- 1 4. (canceled)
- 1 5. (original) The method of claim 1, in which there are 128 tones and two
- 2 groups.

- 6. (original) The method of claim 2, in which a duration of each FSK symbol
- 2 depends on a spacing of the tones.
- 1 7. (original) The method of claim 1, further comprising:
- detecting the FSK symbols in a OFDM receiver.
- 8. (original) An OFDM transmitter for generating FSK symbols in a
- 2 communications network, comprising:
- means for partitioning a plurality of complex values representing
- 4 OFDM tones into a plurality of groups;
- 5 means for assigning a distinct energy to each group of complex
- 6 values;
- an OFDM modulator configured to apply OFDM modulation to the
- 8 plurality of complex values having the assigned distinct energies to generate
- 9 FSK symbols corresponding to the plurality of groups, in which a duration
- of each FSK symbol is smaller or equal to a duration of an OFDM symbol
- 11 for which the OFDM modulator is designed; and
- means for transmitting the FSK symbols serially.